

PTS PRECISION TEST SYSTEMS

PTS50 10 MHz Distribution Amplifier



Key Features

- 10 MHz Input
- AGC Controlled
- 5 Sinewave Outputs
- 1 Squarewave Output
- Slave Output
- Low Phase Noise
- High Isolation
- MTBF over 30 years
- AC or DC power
- CE Marked

General Description

The PTS50 can be used to synchronize up to six instruments to a 10 MHz reference input. The PTS50 incorporates AGC (automatic gain control) so that a 10 MHz input can be varied from -10 dBm to +20 dBm without the outputs changing by more than 0.4 dB. Inputs as low as -30 dBm still produce a useable output. The pure sinewave output (harmonics are 70 dB down) enables the PTS50 to work in the most demanding applications. The output frequency accuracy is exactly the same as the input frequency accuracy.

Outputs

There are five, 10 MHz, sinewave outputs. Each 10 MHz output is isolated from the input and each other. Therefore the reference oscillator connected to the PTS50 input is protected against load variations, short circuits etc. that may be applied to the outputs.

A sixth squarewave output can be switched in frequency from 10 MHz, 2 MHz, 1 MHz, 100 kHz and 1 Hz. This output is ideal for instruments that do not use a 10 MHz timebase. A rear slave output can be connected to a second PTS50 (or more) to give up to twelve outputs (or more). See "Applications" below.

Applications

The PTS50 10 MHz Distribution Amplifier is ideal for use in calibration or standard laboratories, radio repair workshops or production facilities. By using the rear slave output, many PTS50's can be connected together to give multiple outputs

Miscellaneous Information

The PTS50 is a highly reliable unit with a MTBF (based on real data) of over 30 years. The PTS50 is housed in a fully screened steel case and operates from a 115 VAC or 230 VAC supply or external 12 V DC. The PTS50 is CE marked for sale within the EEC.

Options

The PTS50 series can be modified upon special request to work at different frequencies than 5 MHz. For example the PTS50-15 accepts a 15 MHz input and has 15 MHz outputs. Refer to the relevant brochures for more information. Other options include 19" rack mount case and alarm relay outputs (relay activated on loss of input signal or AC/DC power).

PTS50 SPECIFICATIONS

Specification Parameter	Specification	Comments
Input		
Frequency	10.000 MHz	
Bandwidth (-3 dB)	> ± 250 kHz	
Impedance	50 Ω	
Input VSWR	< 1.30 @ 10 MHz	
Input Level Range (5 MHz input)	+20 dBm to -10 dBm	Output Changes by < 0.4 dB
Outputs 1 to 5		
Output Waveform	Sinewave	50 Ω BNC Connector
Output Frequency	Same as the input frequency	
Output VSWR (50 Ω)	< 1.7:1 @ 10 MHz	
Output level (5 MHz input)	From 0 dBm to +12 dBm	Each output internal adjustable
Harmonic Distortion at 5 MHz	-70 dBc	Output set to +10 dBm
Jitter	< 2 ps rms	
Input to Output Isolation	> 100 dB	Typical
Output 6		
Output Waveform	Squarewave	Front Panel BNC Connector
Level	0 - 5V (open circuit) 0 - 2.7 V (50 Ω)	TTL Compatible
Frequency	10, 5, 2, 1, 0.1 MHz and 1.0 Hz	
Risetime	< 25 ns	At 1 MHz
Jitter (1 second, Allan Deviation)	< 5 x 10E-13	Typically < 3 x 10E-13 / 1 second
Output 7 (Slave Output)		
Output Waveform	Sinewave	Rear Panel BNC Connector
Phase Noise (Typical)		
At 10 Hz Offset	-130 dBc/Hz	Measurement uncertainty ± 4 dB
General		
Power (AC)	115 VAC or 230 VAC ± 10%	15 Watts max
Power (DC)	11-13 VDC @ 0.7 Amps	
Size and weight	215 x 265 x 35 mm and 2.8 kg	Width x Depth x Height
Ambient Operating Temperature	-10°C to +50 °C	
Options		
Option 01	19" Rack Mount case	
Option 02	Traceable Calibration Certificate	Traceable to UKAS or NIST
Option 03	Alarm Relay Outputs	Activated if input signal/power is lost

Precision Test Systems		
Head Office - UK	South Africa	USA
Precision Test Systems LTD 40 Holkham Avenue, South Woodham Ferrers Essex, CM3 7AU, England Tel: +44 (0) 870 368 9608 Fax: +44 (0) 1245 330030 Email: uksales@ptsyst.com Web: www.ptsyst.com	Precision Test Systems cc Randburg Gauteng South Africa Fax: 08651 58198 Email: sasales@ptsyst.com Web: www.ptsyst.com	Precision Test Systems 14781 Memorial Drive, Suite # 981 Houston Texas, 77079, USA Tel: 1 888 876 4804 Fax: 1 832 201 6564 Email: usasales@ptsyst.com Web: www.ptsyst.com

Full specifications available from www.ptsyst.com. Specifications and features subject to change without notice (071211)