

## Copper Tube Crimp Terminals



### Product Overview

- All copper tubes terminals have bell mouth entry for ease of cable insertion.
- All terminals have inspection holes to check cable is properly inserted before crimping
- Copper tube splices, four hole transformer fixing, long palm, right angle, blank terminals, copper pins, dissimilar copper splices and flag terminals also available on request.
- Sizes above 400mm<sup>2</sup> available on request.
- Other Stud sizes available on request.

### Specification:

Material: High Conductivity copper to BS 2871

Purity: > 99.9%

Coating: Bright electro-tin plating to BS 1872.

Entry: Bell-mouth easy entry.

Barrels: Internal Barrel diameters suit standard cables as defined in BS 6360.

## Copper Tube Terminals

Part No.	Conductor Cross-sectional Area (mm <sup>2</sup> )	Stud Size (mm) (Please Specify ) (Eg. DX 10-5)
DX 1.5	1.5	4, 5
DX 2.5	2.5	4, 5, 6
DX 4	4	4, 5, 6
DX 6	6	4, 5, 6, 8, 10
DX 10	10	5, 6, 8, 10, 12
DX 16	16	5, 6, 8, 10, 12
DX 25	25	5, 6, 8, 10, 12
DX 35	35	6, 8, 10, 12
DX 50	50	6, 8, 10, 12, 14, 16
DX 70	70	6, 8, 10, 12, 14, 16
DX 95	95	8, 10, 12, 14, 16
DX 120	120	8, 10, 12, 14, 16
DX 150	150	10, 12, 14, 16, 20
DX 185	185	10, 12, 14, 16, 20
DX 240	240	10, 12, 14, 16, 20
DX 300	300	10, 12, 14, 16, 20
DX 400	400	10, 12, 14, 16, 20